

ALER JQ

PIR motion sensor



[V] 220-240 AC	[Hz] 50/60	[VA] 1200	IP 44			
F	[m] max 12	[°] H160/V20	[s]-[min] 8-7	PIR	[lx] 3-2000	[°C] -20÷40
	[mm²] 1÷2.5	CE	EAC			

ALER JQ-30-W

	[VA]		[°]	[s]-[min]	SENSOR
ALER JQ-30-W 00460	1200	wall mounted	H160/V20	8-7	PIR
ALER JQ-30-B 00461	1200	wall mounted	H160/V20	8-7	PIR

Kanlux ALER JQ is a motion detector whose maximum detection range comes to 12 metres. You can set adjustments of the lighting time and light intensity level at which the detector works.

- Material: plastic




ALER JQ-30-W



ALER JQ-30-B

ALER JQ

PIR motion sensor



ALER JQ-30